



• **CH32: (Litetouch) Dual Colour Halo Ring & Touch Pad Switch**

Comprising a dual-colour Halo ring and switch combination that can be used with all Clockaudio through-table products, the Litetouch allows users to easily identify the status of microphones, as well as mute the units for privacy.

With no moving parts, the switch is touch-sensitive, so there are no clicking noises when switching from one status to another. Both the switch and the Halo have been designed to operate remotely with all popular brands of electronic system control, so an integrator has complete freedom to assign function and LED colour.

Importantly, the Litetouch can be easily retrofitted to any Clockaudio through-table microphone product.

Features:

- Designed for remote switching
- Housing 32 LEDs to give 360° illumination
- 12, 24v DC operation
- Current consumption 40mA
- Retrofittable to all Clockaudio through-table microphones
- Fitted with 5 way socket terminal block supplied with fixing screws



Specifications:

Model:	CH32
Type	Dual Colour Halo Ring & Touch Sensitive Switch
LED Colour	Red and Green
Operating Voltage	12, 24v DC (Regulated). For 24v DC operation a 300Ω 1W resistor must be put in series with both the green and red LED wires.
Current Consumption	40mA
Termination	5 way socket terminal block (with fixing screws)
Dimensions	39(W) x 5(H) x 48(D) xmm
Hole Diameter	25 mm