

DIGITAL AMPLIFIER



FEATURES

- High power, high performance 4 channel Class-D
- Advanced protection circuit
- SMPS(Switch Mode Power Supply)
- Powerful and delicate sound
- LED display
- Balance input
- PRIORITY input

SPECIFICATIONS

		SCM-6000V
Rated Output Power	8 Ω per channel, stereo	300 W
	4 Ω per channel, stereo	600 W
Gain(rated output power@8 Ω)		32 dB
Input Sensitivity(rated output power@8 Ω)		1.23 Vrms
Frequency Response		20 Hz~20 kHz, 0 dB \pm 3 dB
THD (1/8 rated output power@8 Ω)		Less than 0.1 %
S/N (rated output power@8 Ω , 20 Hz~20 kHz)		More than 100 dB
Weight(SET)		7.2 kg/15.9 lbs
Dimensions(W×H×D)		482×88×397 mm/19×3.5×15.6 in

* Specifications and design are subject to change without notice.

interM

DIGITAL AMPLIFIER