

## ○ PAM-340A / PAM-480A: 340W, 480W Modular Mixer Amplifiers


Larger power/output versions of the PAM-120A, however with a number of subtle differences;

No 24v DC power option, no low impedance 4Ω loudspeaker option, but with the addition of a multi-zone paging mic interface allowing simple 5 zone paging using optional RM-05A (see page 16 for details).

### Features:

- 6 Mic/line inputs (3 pin XLR)
- 2 Module option slots (see page 16 for tuner and CD modules)
- Link input (¼" jack)
- Amp input (¼" jack)
- Pre amp out (¼" jack)
- External chime (screw terminal)
- Zone mic interface (15 pin D-type)
- External mute (screw terminal)
- Individual EQ per input channel
- Individual phantom power (per mic input)
- Priority mic 1, mic 2 (switchable)
- 5 Zone loudspeaker selector
- Bar graph VU metre
- Optional 19" rack kit (BKT-PAM)
- 3U high
- Emergency message facility  
*(Only available as custom factory install - contact the sales office on 0115 9770075 for details and prices.)*

### ○ 19" Rack Mount Bracket Option: BKT-PAM Bracket



### Specifications:

Model:	PAM-340A:	PAM-480A:
Output Power	340W RMS @ 100v	480W RMS @ 100v
Inputs	6 x Mic/Line (3 pin XLR)	6 x Mic/Line (3 pin XLR)
Priority	Mic 1, Mic 2	Mic 1, Mic 2
Phantom Power	22v DC individually switched per input channel	22v DC individually switched per input channel
Input Sensitivity/Impedance	Inputs 1~6 -60dB~-16dB 1mV/10kΩ	Inputs 1~6 -60dB~-16dB 1mV/10kΩ
Frequency Response	80Hz~20KHz	80Hz~20KHz
Power Requirement	230v AC 50Hz	230v AC 50Hz
Dimensions	420(W) x 132(H) x 360(D)mm	420(W) x 132(H) x 360(D)mm
Weight	13.5kg	15.5kg

