

◦ RM-05A: Remote 5 Zone Microphone

The RM-05A is designed to be exclusively used with the Inter-M PAM-340A & PAM480A Mixer Amplifiers and provides the facility of a simple 'one cable' multi-zone solution. The paging unit also includes output level LED VU metre, gain/level control and chime facility. Power is provided by the host amplifier.

Features:

- Individual channel selection or all-call
- Flexible condenser-type gooseneck microphone
- Pre-announcement chime
- LED output level indicator

Specifications:

Model:	RM-05A:
Output Level/Impedance	+4dB(unit gain)/600Ω, BAL
THD	Less than 0.1%
Speaker Control Terminal & Switch	5 Channel
Type	Condenser Microphone
Polar Pattern	Unidirectional
Frequency Response	100Hz~16KHz
Impedance	Max 680Ω
Sensitivity(0dB=1V/0.1Pa at 1kHz)	-47dB±3dB
Current Consumption	Max 0.5mA
S/N Ratio	More than 60dB
Standard Power Supply	DC 1.5v
Power Source	DC 24v (via D-Sub connector)
Dimensions	194(W) x 60(H) x 205(D)mm
Weight	1.1kg

