

Akuvox EP10(869)

For use in conjunction with the Akuvox C315S, C317S & X7HD Answering Intercom Panels, the EP10(869) Telecare Call Pendant allows users to remotely make an emergency call to a designated number.

Use the telecare pendant to make an emergency call to a designated family member or twenty-four hour service centre.

The telecare pendant can also be programmed to remotely unlock doors for visitors.



Features:

- Hygienic, easy to clean
- Bidirectional transceiver (TRX)
- 2-colour LED to indicate a Receive abnormal (red) and acknowledgment of receipt (green)
- Technical monitoring (battery monitoring and daily report)
- Battery (button cell CR2032 Lithium 3V) can be replaced by the customer
- Battery life: up to 2 years under normal use
- Coverage: up to 30 m in buildings (depending of the building structure), up to 80 m outdoors

Compatible panels:

- C315S(869)
- C317A(869)
- C317S(869)
- X7HD(869)

Specifications:

Description	EP10(869)
Dimensions (WxDxH):	43 x 57 x 20 mm
Housing material:	ABS & Silica
Radio receiver system:	869.2 MHz
Coverage:	up to 250m outdoors/up to 30m in buildings
Useful life of the battery:	up to 2 years
Operating temperature range:	0°C - 40°C
Length of the cord:	approx.47.5 cm
Max.Output Power:	2dBm
Frequency Range:	869.1MHz to 869.3MHz
Weight:	18 g (without cord)