

• **Elma BM 117: 2000A AC Clamp Meter**

The new Elma BM 117 is a handy Clamp Meter capable of measuring flow of up to 2000A AC.

The meter measures current, voltage, capacitance, resistance, continuity and is fitted with large display, automatic range selection, touchless pole and data hold.

The Elma BM 117 is equipped with brand new intelligent "Auto Check" feature, which automatically detects and selects AC voltage, DC voltage and reviewing/resistance.

Features:

- Measures Current flow of up to 2000A
- Intelligent Auto Check feature detects and selects AC/DC voltage, resistance
- Compliant with IEC 61010-1 CAT III 600V
- Supplied complete with storage case, test leads, battery and manual

 TSI Code: 395663505



Specifications:

Model:	Elma BM 117
Power	0-400 AC-2000A
Resolution	0.1 ~ 1A
Accuracy	±1.5% + 5D
Voltage	0, 6, 60, 600v AC/DC
Capacitance	0, 100N, 1000N, 10µ, 100µ, 2000µF
Resistance	0, 600, 6k, 60k, 600k, 6MΩ
Continuity Test	Less than 20Ω audible alarm
Display	3 5/6
Max Display	5999
Clamp Length	45mm
Battery	2 x 1, 5v AAA (included)
Dimensions	224(H) x 78(W) x 40(D) mm
Weight (Net)	0.22kg
Weight (Gross)	0.40kg