



Portable Infrared Receiver

IR-RX2

Our Portable Infrared Receiver is a four channel receiver, compatible with our infrared transmitters using frequencies 2.3MHz and 2.8MHz. It features automatic gain control and high sensitivity for incoming infrared signals.

The receiver uses rechargeable batteries, and is a versatile and sturdy unit which requires either headphones or an assistive hearing neck loop.

What's Included:

- Portable Infrared Receiver
- Lanyard with Clip
- Belt Clip
- 2x Rechargeable Batteries

Accessories

- 5 Bay Infrared Receiver Charger (see page 10)
- Infrared Neck Loop (see page 10)
- Underchin Headphones (see page 11)
- Headphones (see page 11)

Technical Data:

Receiver Frequencies	2.3MHz / 2.8MHz / 3.3MHz / 3.8MHz
Modulation	FM broadband
Battery Type	2x AAA rechargeable batteries; type NiMH, 1.2V 750 mAh
Frequency Response	60Hz to 12kHz \pm 3 dB
Signal-to-Noise Ratio	54dB not weighted
Usage Period	20 hours
Maximum Output	6mW
Settings	Volume Adjustment
	4 Channel selection - Rotary Control

Physical Data:

Dimensions	Height – 112mm (4.40") Width – 70mm (2.75") Depth – 22mm (0.86")
Weight	200g (0.44lbs)
Finish	Black

Product Code:

Portable IR Receiver	IR-RX2
----------------------	--------