

## v1.3 HDMI 4x4 Matrix with built in HDMI over CAT6 outputs



All the PUMA, HDMI over CAT5e/6 transmitters and receivers are the perfect solution to extend HDMI signals via CAT cabling up to 30m. The PU-O products within the PUMA range combine HDMI over CAT5e/6 (PUMA) & HDMI Matrix switcher (ORBIT) to provide versatility to HDMI installations. The PU-O4H4C HDMI matrix has 4 HDMI input and 4 CAT transmitter outputs. Each of the four HDMI sources can be directed to any one of the four CAT outputs, so each display can show the same or a different source.

### Features

- v1.3 HDMI, HDCP 1.1, DVI 1.0 compliant.
- HDMI 4x4 Matrix with built in HDMI over CAT6 outputs.
- Resolutions supported: PC - VGA to UXGA ; HDTV - 480i to 1080p + 1080p24fps.
- High Definition audio supported: Dolby TrueHD, Dolby Digital Plus, DTS-HD Master Audio + LPCM.
- The HDMI input is compensated, clock / phase adjusted, and jitter eliminated so the output is a brand new standard HDMI signal.
- RS-232 and IR remote control, plus IR extender.
- Supports Deep Colour (10/12 bit).
- LED indicators.

E. & O.E

### Specifications

Input:	4 x HDMI female ports 1 x IR Jack
Output:	8 x CAT5e/6 (2 for each output) 1 x IR Jack, 1 X RS-232
Power:	5V/6A, DC (US/EU standards, CE/FCC/UL certified)
Dimensions:	438mm (W) x 175mm (D) x 44mm (H)
Gross Weight:	3440g
Net. Weight:	3080g
Packaging:	Boxed

