

• **Volt Stick EX230: ATEX Voltage Indicator (230v)**

The IECEx & ATEX-Approved version of the Volt Stick 230.

The original and still the best, Volt Stick is an instant tester for safely checking the presence of an AC voltage, without making any disconnections in cables, wall sockets, fuses, circuit breakers, junction boxes, etc. No current flow is needed for correct operation.

The red indicator in the tip will illuminate on detection of AC voltage simply by applying the tip close to any connection point, or moving it along any insulated cable.

All Volt Stick models are fully approved to IEC 61010-1, CAT111 1000v AC and CE.

Features:

- Locates breaks in cables
- Detects blown fuses inside plugs or fuse holders
- Distinguishes between live and neutral wires in both single and three-phase supplies
- Identifies voltage-carrying cables in junction boxes
- Identifies faulty in-line switches
- Locates defective in-series light bulbs
- Optimised for 230v AC



Specifications:

Model:	Volt Stick EX230
Voltage range	220 ~ 230v AC
Sensitivity	Indicator will illuminate at 4mm distance of a 2.5mm conductor carrying 220v
Response Time	Immediate
Intrinsically Safe	Yes
Power Requirements	2 x Standard AAA alkaline batteries (supplied)
Relative Humidity	80% @ 30°C, 50% @ 40°C
Operating Temperature	-20 ~ +50°C
Overvoltage	CAT III, 1000v AC
Dimensions	145(L) x 18(Ø) mm
Weight	0.035kg (including batteries)