

- **Volt Stick SOUND:** Instant Voltage Tester with Sounder (230v)

The Volt Stick SOUND features a detection buzzer for even greater clarification. Also ideal for 'detection round corners', in bright daylight and in awkward out of sight areas. High visibility green tube for ease of identification if dropped or hidden in the toolbox.

Features:

- Added Sounder feature
- Locates breaks in cables
- Detects blown fuses inside plugs or fuse holders
- Distinguishes between live and neutral wires in both single and three-phase supplies
- Identifies voltage-carrying cables in junction boxes
- Identifies faulty in-line switches
- Locates defective in-series light bulbs



Specifications:

Model:	Volt Stick SOUND
Voltage range	200 ~ 1000v AC
Sensitivity	Functions @ 4mm distance from 2.5mm ² conductor carrying 220v AC
Response Time	Immediate
Intrinsically Safe	No
Power Requirements	2 x Standard AAA alkaline batteries (supplied)
Relative Humidity	80% @ 30°C, 50% @ 40°C
Operating Temperature	-20 ~ +50°C
Overvoltage	CAT III, 1000v AC
Dimensions	145(L) x 18(Ø) mm
Weight	0.04kg (including batteries)